



MAIN FEATURES

- ✓ LOAD: 6A TUNGSTEN; 6A INDUCTIVE LOAD
- ✓ IP54 RATED SUITABLE FOR EXTERNAL APPLICATIONS (WHEN INSTALLED)
- ✓ SWITCHES AT 70 LUX
- ✓ CLASS II

SAFETY INFORMATION

This luminaire must be installed and operated in full accordance with the information contained in this document. Failure to do so will invalidate any warranty.

INSTALLATION MUST BE CARRIED OUT BY A QUALIFIED PROFESSIONAL AND FOLLOW RELEVANT SAFETY STANDARDS, WIRING AND BUILDING REGULATIONS.

WARNING

Switch off power before installation!

Switch the power supply back on after installation & circuit examination. Professional electricians are required for installation & maintenance.



INSTALLATION INSTRUCTIONS

Carefully choose the correct position to install the photocell considering the following guidelines:

1. Where possible there should be a clear view of the sky.
2. Be away from the view of the light source the unit is to control.
3. Securely fix the photocell through a 20mm clearance hole using the locking ring and gasket which should be positioned on either side of the hole with the gasket on the outside of the hole to form a water tight seal.
4. Terminate the 3 cables observing the correct connections:
"Brown" = Live (Supply In)
"Blue" = Neutral
"Red" = Switch (Load Out)

OPERATING & TESTING

1. The photocell always powers up in the "On" position, if in bright daylight it will switch off within 15 seconds and normal operation will then resume.
2. To test for correct operation cover the photocell. After a short delay of 5-15 seconds, the photocell will operate and power will be applied to the load. If tested in bright daylight after a similar delay the photocell will turn off the power to the load when the cover is removed.

FAULT FINDING

1. The load stays on: The photocell is in a shady or dark position. The neutral is not connected.
2. The load is flashing, strobing or switching on and off repeatedly through hours of darkness. The photocell is too close to the light source it is controlling.
"Live (BROWN)" & "Load (RED)" are reversed

REMOTE PHOTOCELL

Product Code: HSPC2

Date: April 2025

Version: 1

LIMITED PRODUCT WARRANTY

This device is under warranty under normal use and service for a period of 2 years from the date of purchase. The company will not be obligated to repair or replace parts which are found to be in need of repair because of misuse, damage or alterations that have occurred after the date of purchase. Send the product with proof of purchase, postage and return postage prepaid, to your local distributor. The liability of the company arising from the sale of this product shall not in any case exceed the cost of replacement of the product and in no case shall the company be liable for consequential loss or damages resulting from the failure of the product.

HISPEC ELECTRICAL PRODUCTS LTD. SHALL HAVE NO LIABILITY FOR ANY PERSONAL INJURY OR PROPERTY DAMAGE, OR ANY SPECIAL, INCIDENTAL, CONTINGENT OR CONSEQUENTIAL DAMAGE OF ANY KIND, RESULTING FROM A DEFECTIVE PRODUCT. THE EXCLUSIVE REMEDY FOR BREACH OF THE LIMITED WARRANTY CONTAINED HEREIN IS THE REPAIR OR REPLACEMENT OF THE DEFECTIVE PRODUCT BY HISPEC ELECTRICAL PRODUCTS LTD. LIABILITY UNDER ANY OTHER REMEDY PRESCRIBED BY LAW SHALL NOT EXCEED THE PURCHASE PRICE OF THE INDIVIDUAL PRODUCT.

This does not affect your statutory rights.



Waste electrical products should not be disposed of with normal household waste. Please recycle where facilities exist. Check with your local authority or retailer for recycling advice. The new regulation will encourage the recycling of waste from, electrical and electronic equipment (European "WEEE Directive" effective August 2005).

*Warranty Disclaimer - Please note that all lighting equipment must be used in accordance with the instructions provided in this document. Failure to follow these instructions, including but not limited to improper installation, positioning, control, or use of non-recommended accessories, will invalidate the equipment warranty. Always ensure proper safety protocols and the use of certified technicians for setup and operation. * ON SITE WARRANTY SUBJECT TO CONDITIONS AND UK REGIONS ONLY*